

# 4140XMPT PROGRAMMING FORM

Refer to the Installation Instruction's INDEX OF PROGRAMMING FIELDS for numerical list of program fields.

Standard default values are shown in brackets [ ], otherwise default = 0.

Fields shown in italics can be programmed using the #93 Menu mode.

Parentheses ( ) around a field number indicate differences from 4140xmp programming fields.

## SECURITY ACCESS OPTIONS

**\*00** INSTALLER CODE     **(\*15)** KEYSWITCH ASSIGNMENT   
 Enter 4 digits, 0-9 [4140] Enter partition in which keyswitch used, 1-8; [0=disable]

## ASSIGN RESPONSE TYPE FOR ZONES (Enter 00-10; see Response Types box below)

*02	*03	*04	*05	1*01	1*02	1*03	1*04	1*05	1*09	
1 <input type="text"/>	9 <input type="text"/>	17 <input type="text"/>	25 <input type="text"/>	28 <input type="text"/>	33 <input type="text"/>	41 <input type="text"/>	49 <input type="text"/>	57 <input type="text"/>	88 <input type="text"/>	2nd RCVR
2 <input type="text"/>	10 <input type="text"/>	18 <input type="text"/>	26 <input type="text"/>	29 <input type="text"/>	34 <input type="text"/>	42 <input type="text"/>	50 <input type="text"/>	58 <input type="text"/>	89 <input type="text"/>	2nd RCVR
3 <input type="text"/>	11 <input type="text"/>	19 <input type="text"/>	27 <input type="text"/>	30 <input type="text"/>	35 <input type="text"/>	43 <input type="text"/>	51 <input type="text"/>	59 <input type="text"/>	90 <input type="text"/>	1st RCVR
4 <input type="text"/>	12 <input type="text"/>	20 <input type="text"/>	0/0	31 <input type="text"/>	36 <input type="text"/>	44 <input type="text"/>	52 <input type="text"/>	60 <input type="text"/>	91 <input type="text"/>	1st RCVR
5 <input type="text"/>	13 <input type="text"/>	21 <input type="text"/>	97 <input type="text"/>	32 <input type="text"/>	37 <input type="text"/>	45 <input type="text"/>	53 <input type="text"/>	61 <input type="text"/>	Use of 1 or 2 RF RCVRs requires enabling their respective faults (88-91) as troubles (type 5). Enter 00 if no annunciation is desired.	
6 <input type="text"/>	14 <input type="text"/>	22 <input type="text"/>	95 <input type="text"/>	(1+*)	38 <input type="text"/>	46 <input type="text"/>	54 <input type="text"/>	62 <input type="text"/>		
7 <input type="text"/>	15 <input type="text"/>	23 <input type="text"/>	96 <input type="text"/>	(3+*)	39 <input type="text"/>	47 <input type="text"/>	55 <input type="text"/>	63 <input type="text"/>		
8 <input type="text"/>	16 <input type="text"/>	24 <input type="text"/>	99 <input type="text"/>	(#+#)	40 <input type="text"/>	48 <input type="text"/>	56 <input type="text"/>	64 <input type="text"/>		

NOTES: 97= Poll Loop Short; 88 & 90 = RCVR not receiving transmitter signals. 89 & 91 = RCVR not responding, bad conn. to panel.

**RESPONSE TYPES:** 00 = Disabled zone; 01 = Entry/Exit #1; 02 = Entry/Exit #2; 03 = Perimeter; 04 = Interior Follower; 05 = Day/Night; 06 = 24 hour Silent Alarm; 07 = 24 hour Audible Alarm; 08 = 24 hour Auxiliary; 09 = Fire; 10 = Interior, Delay;

## DESIGNATE RIGHT LOOP FOR MULTIPLEX EXPANSION 1=yes; [0=no]

<p><b>*06</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 10 11 12 13 14 15 16</p> <p><b>*07</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 17 18 19 20 21 22 23 34</p> <p><b>*08</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 25 26 27 28 29 30 31 32</p> <p><b>*24</b> 4190WH TAMPER DISABLE <input type="checkbox"/> 1=disable; [0=enable]</p> <p><b>*86</b> ZONE EXPANDER DEVICE <input type="checkbox"/> 1=only one 4208 installed for zones 10-17; [0=more than one 4208 or other devices]</p>	<p><b>1*10</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 33 34 35 36 37 38 39 40</p> <p><b>1*11</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 41 42 43 44 45 46 47 48</p> <p><b>1*12</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 49 50 51 52 53 54 55 56</p> <p><b>1*13</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 57 58 59 60 61 62 63 64</p>
--	---

## SELECTION OF WIRELESS FOR ZONES 1-63

Enter "1" to enable a zone as wireless; 0=non-wireless

<p><b>1*18</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 1 2 3 4 5 6 7 8</p> <p><b>1*19</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 9 10 11 12 13 14 15 16</p> <p><b>1*20</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 17 18 19 20 21 22 23 24</p> <p><b>1*21</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 25 26 27 28 29 30 31 32</p> <p><b>1*22</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 33 34 35 36 37 38 39 40</p> <p><b>1*23</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 41 42 43 44 45 46 47 48</p> <p><b>1*24</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 49 50 51 52 53 54 55 56</p> <p><b>1*25</b> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/></p> <p>ZONES: 57 58 59 60 61 62 63</p>	<h2>MISCELLANEOUS WIRELESS OPTIONS</h2> <p><b>1*26</b> FIRST RF RECEIVER SELECT <input type="checkbox"/> 1=yes; [0=no]</p> <p><b>1*27</b> SECOND RF RECEIVER SELECT <input type="checkbox"/> 1=yes; [0=no]</p> <p><b>1*28</b> RF TRANSMITTER LOW <input type="checkbox"/> 1=immediate; [0=when disarmed] BATTERY ANNUN. Must be "1" for UL</p> <p><b>1*29</b> RF TRANSMITTER LOW <input type="checkbox"/> 1=enable; [0=disable] BATTERY REPORT ENABLE Must be "1" for UL</p> <p><b>1*30</b> RF RECEIVER SUPERVISION <input type="checkbox"/> CHECK-IN INTERVAL 02-15 times 2 hours; 00 disables supervision [6] Max. "6" (12 hr) for UL</p> <p><b>1*31</b> RF TRANSMITTER <input type="checkbox"/> CHECK-IN INTERVAL 02-15 times 2 hours; 00 disables transmitter supervision [12] Max. "6" (12 hr) for UL</p> <p><b>1*44</b> WIRELESS KEYPAD <input type="checkbox"/> TAMPER DETECT ENABLE 1=enable; [0=disable]</p> <p><b>(1*48)</b> WIRELESS KEYPAD ASSIGNMENT <input type="checkbox"/> 0=disable; enter partition in which RF keypad used, 1-8.</p> <p><b>1*49</b> DISABLE TROUBLE SOUNDER <input type="checkbox"/> FOR RF SUPERVISION [1=disable]; 0=enable. Must be "0" for UL.</p>
---	---

## AC LOSS OPTIONS

**\*17** AC POWER LOSS SOUNDING  1=yes; [0=no]

**\*18** AC POWER LOSS ALARM  1=yes; [0=no]

**\*19** AC RANDOMIZE  1=randomize 10-40 min.; [0=no]

**\*28** POWER UP IN PREVIOUS STATE   
[1=yes; 0=no; "1" for UL.